



NOTES: (1) Two SWM modules snap directly into the E2 SWM Expander. Coaxial (RG6) cables are required to connect the power to the Legacy 3 output of each SWM. (2) Connect up to 16 satellite tuners (8 DVRs or up to 16 regular receivers) to the two SWM8 switches (up to 8 per SWM). Use weaKnees/DIRECTV-approved SWM splitters to connect more than one receiver to the SWM1 or SWM2 port of each SWM. (3) Do not use B-Band converters with SWM. (4) Perform a red-button reset after installing each receiver. (5) After connecting all of your receivers, power them on one at a time. (6) One coax line from the splitter into the SWM/FTM port will power both tuners in an HR20/HR21. (7) If connecting to an off-air tuner, split the off-air signal using a standard splitter and connect each output to the off-air input of each SWM. A standard diplexer is not recommended to split the off-air and the satellite signal at the receiver. Instead, weaKnees.com recommends a special diplexing high-frequency splitter. From the output of the splitter, connect one leg to the SWM/FTM port and the other to the off-air antenna input. Please contact us for assistance.